

Small generator check card

*"Periodic check and service are very important for keeping the engine in good condition.
That chart below indicates what checks to make and when to make them"*

Description	Every time	20 HRS	100HRS	200HRS	300HR
Check and refill fuel	x				
Drain out fuel if needed (if generator is standing for a long period drain fuel before operation)			x		
Check and refill engine oil	x				
Check for oil leakage	x				
Check and tighten fastening parts			x	x tighten cylinder head bolts	
Check engine valve clearance			x		
Replace engine oil		x	x	x	x
Clean engine oil filter			x	x	x
Replace air cleaner	more frequent if when used in dusty areas		x	x	x
Clean fuel filter			x	x	x
Check fuel injector pump				x	
Check nozzle				x	
Check fuep pipe				x replace if leaking	
Adjust clearance of intake/exhaust valves				x	
replace pisotn rings depending on work load					x
check carbon brushes and slip ring			x		

Directors: H van As (CEO) H.M. van As (Managing) L.E. van As E. van As

