

**COMPONENTS 2005****(PTY) LTD****t/a ENGINE & HEAVY DUTY COMPONENTS****HEAD OFFICE JOHANNESBURG**

Tel: +27 (0)11 870 5000
 Fax to Mail: 086 676 6628
 Cnr Hubert & Marshall Streets,
 Marshalltown, Johannesburg 2001
 PO Box 6541 Johannesburg, 2000,
 South Africa
 ehd@ehd.co.za

BLOEMFONTEIN

Tel: +27 (0)51 430 5404
 17 Krause Street, Oranjesig
 South Africa
 ehdbloem@ehd.co.za

CAPE TOWN

Tel: +27 (0)21 510 0567
 25 Bellray Business Park
 Ampere Street, Stikland Industrial
 Cape Town, 7530
 PO Box 1037, Milnerton, 7435
 South Africa
 ehdcapetown@ehd.co.za

DURBAN

Tel: +27 (0)31 700 1160
 Unit 3, Hillmax
 31 Hillclimb Rd, Westmead 3610
 PO Box 1054 Nagina 3604,
 South Africa
 ehd.dbn@ehd.co.za

MDG6000S

	MDG6000S
Frequency (Hz)	50
Max. AC Output (kw)	5.0/5.5
Cont. AC Output (kw)	4.2
Rated Current (A)	20.5
Voltage (V)	110;120;220;110/220;120;240
D.C. Output (V-A)	12/8.3
Power Factor	1
Engine Model	MD186FG
Displacement (cc)/(cu.in)	418/25.5
Engine Speed (rpm)	3000/3600
Engine Starting System	Electric
Lube Oil Capacity (L)/(US.Gal)	1.65/0.44
Fuel Tank Capacity (L)/(US.Gal)	16/4.22
Operational Capacity (hr)	7.8
Dimensions (LxWxH)(mm)	900x520x700
Net Weight (kg)/(ibs)	150/330.693
Noise Level at 7 M (dBA)	70

Proud Member of: