

**COMPONENTS 2005****(PTY) LTD****t/a ENGINE & HEAVY DUTY COMPONENTS****HEAD OFFICE JOHANNESBURG**

Tel: +27 (0)11 870 5000
 Fax to Mail: 086 676 6628
 Cnr Hubert & Marshall Streets,
 Marshalltown, Johannesburg 2001
 ehd@ehd.co.za

BLOEMFONTEIN

Tel: +27 (0)51 430 5404
 17 Krause Street, Oranjesig
 South Africa
 ehdbloem@ehd.co.za

CAPE TOWN

Tel: +27 (0)21 510 0567
 25 Bellray Business Park
 Ampere Street, Stikland Industrial
 Cape Town, 7530
 ehdcapetown@ehd.co.za

DURBAN

Tel: +27 (0)31 700 1160
 Unit 3, Hillmax
 31 Hillclimb Rd, Westmead 3610
 ehddurban@ehd.co.za

**MDG6000**

Frequency	50
Max AC Output (kW)	5
Cont. AC Output (kW)	4.5
Rated Current (A)	20.5
Voltage (V)	110;115;120;220;110/220;115/230;120/240
D.C. Output(V-A)	12/8.3
Power Factor	1
Engine Model	MD186FG
Displacement (cc) / (cu.in)	418/25.5
Engine Speed (rpm)	3000
Lube Oil Capacity (L) / (US.Gal)	1.65/0.44
Fuel Tank Capacity (L) / (US.Gal)	12.5/3.3
Dimensions (LxWxH) (mm)	740x475x590
Net Weight (kg) / (lbs)	88/194.007

Proud Member of: