

HEAD OFFICE JOHANNESBURG

Tel: +27 (0)11 870 5000

Fax to Mail: 086 676 6628

Cnr Hubert & Marshall Streets,
Marshalltown, Johannesburg 2001
ehd@ehd.co.za

BLOEMFONTEIN

Tel: +27 (0)51 430 5404

17 Krause Street, Oranjesig

Bloemfontein, 9301
ehdbloem@ehd.co.za

CAPE TOWN

Tel: +27 (0)21 510 0567

25 Bellray Business Park

Ampere Street, Stikland Industrial
Cape Town, 7530
ehdcape@ehd.co.za

DURBAN

Tel: +27 (0)31 700 1160

Unit 3, Hillmax

31 Hillclimb Rd, Westmead 3610
ehddurban@ehd.co.za

Co. Reg No. 2005/019759/07

Export Code. 20535466

Vat No. 4790223137

	MDG6000S
Frequency (Hz)	50
Max. AC Output (kw)	5.0/5.5
Cont. AC Output (kw)	4.2
Rated Current (A)	20.5
Voltage (V)	110;120;220;110/220;120;240
D.C. Output (V-A)	12/8.3
Power Factor	1
Engine Model	MD186FG
Displacement (cc)/(cu.in)	418/25.5
Engine Speed (rpm)	3000/3600
Engine Starting System	Electric
Lube Oil Capacity (L)/(US.Gal)	1.65/0.44
Fuel Tank Capacity (L)/(US.Gal)	16/4.22
Operational Capacity (hr)	7.8
Dimensions (LxWxH)(mm)	900x520x700
Net Weight (kg)/(lbs)	150/330.693
Noise Level at 7 M (dBA)	70

Proud Member of:


Manufacturer's names, numbers, symbols, photos and descriptions are used for reference purposes only and it is not implied that the parts referred to are the products of those manufacturers. Warranty conditions are available on our website www.ehd.co.za